

1954 Ford AM/FM Stereo Radio

- Depth behind dash is 2.5" at shafts
- Dimensions: 8.75" W x 2.5" H x 2.75" D
- 11.5 - 16.0 volts DC negative ground input - can be operated on 6 volts with power inverter



- Maximum power = 180 watts RMS (45 watts x 4 speakers 4Ω, 14.4V, 1kHz)
- Do not use original speakers
- Uses original antenna
- Sensitivity (FM S/N 30dB) typ 5 dBμ, (AM S/N 20dB) typ 29 dBμ
- Digitally tuned receiver with analog display
- Standard (Motorola) antenna jack ½" D-shafts on controls for mounting (same size and thread as original shafts)
- All controls easily accessible. Volume, Bass, Treble, Balance, Fader and Tuning from original looking controls
- Memory retention (presets, fader and band settings) more than 40 years with power disconnected
- 3 RCA jacks for left channel, right channel and sub-woofer line outs
- 3.5 mm phone jack for input from iPod, satellite radio or MP3 player
- Switch selectable for 1,2,3 or 4 speakers
- Switch selectable for North America or Europe mode
- Includes a 6 foot 3.5mm male-to-male auxiliary cable with every radio



ANTIQUE AUTOMOBILE RADIO, INC.

700 Tampa Road Palm Harbor, FL 34683 USA

727.785.8733 Sales@RadiosForOldCars.Com

www.radiosforoldcars.com