

1962 (late) and 1963 Ford Fairlane AM/FM Stereo Radio

- Small size, BIG features!
- Looks original but offers today's technology
- 2¾" case depth allows room for air conditioning
- Analog controls look and feel like the original radio
- Chrome dash plate (as shown) included



- Black plastic pushbuttons and outer knobs like the original
- All controls easily accessible. Volume, bass, treble, balance, fader and tuning from original-looking controls
- AM dial scale in foreground looks original with FM dial scale in background
- LED dial lights will never need replacing
- Digitally tuned AM/FM stereo front end provides stable, high quality reception
- 11.5-16.0 Volts DC Negative Ground only
- Maximum power = 180 watts RMS (45 watts x 4 speakers 4Ω, 14.4V, 1kHz)
- Do not use original speakers
- Uses original antenna
- 10 presets (5 AM, 5 FM). Digitally tuned receiver with analog display
- Dimensions: 7¾" W x 2½" H. Depth behind dash is 2¾" at shafts
- Standard (Motorola) antenna jack
- Memory retention (presets and other user settings) more than 40 years with power disconnected
- 3 RCA jacks for left channel, right channel and sub-woofer line outs
- 3.5 mm phone jack for input from iPod, satellite radio or MP3 player
- Switch selectable for 1,2,3 or 4 speakers
- Switch selectable for North America or Europe mode
- Includes a 6 foot 3.5mm male-to-male auxiliary cable with every radio



ANTIQUE AUTOMOBILE RADIO, INC.

700 Tampa Road Palm Harbor, FL 34683 USA

727.785.8733 Sales@RadiosForOldCars.Com

www.radiosforoldcars.com